

USB back-to-back extension lead

HIGH GLOSS USB

power and charge your USB devices with sockets protected against damaging surges and spikes

FEATURES

- Two USB ports (3.1A shared)
- Protects valuable electrical equipment from surges and spikes

POWER

- · Unlimited value, 3 year connected equipment warranty
- · Power switch to control the power to your devices
- · LED power and surge indicators
- · Compact back-to-back design
- Wall fixing option



PRODUCT IMAGES







PRODUCT INFORMATION

| Part Number | SRGDU6xPy2 |
|--------------------|---|
| Part Number Note | x = length of cable in metres, y=colour |
| Product Dimensions | Height 74mm x Width 187mm x Depth 62mm |
| Sockets | 6 |

TECHNICAL SPECIFICATIONS

| Standard(s) | This product is certified to applicable British safety standards | |
|---|--|---|
| | BS1363-2, BS62368 | |
| Wall Mounting Option | Yes | |
| Maximum Load (Wattage) | 13A: 3120 Watts, 240 Volts | 1 |
| IF IN DOUBT CONSULT A QUALIFIED ELECTRICIAN | | |

SURGE TECHNICAL DATA

| Protection | 2*14MOV J+1 Gas tube |
|----------------------------|----------------------|
| Maximum Surge Energy | 370 Joules |
| Maximum Surge Current | 12,000 Amps |
| Clamping Voltage | 925 Volts |
| Response Time | <25nS |
| Thermal Cut Out | Yes |
| Protection | L-N, L-E, N-E |
| Surge Protection Indicator | Yes - White |
| Power Indicator | Yes - Blue |

SAFETY WARNING

PLEASE READ CAREFULLY AND USE IN ACCORDANCE WITH OUR SAFETY INSTRUCTIONS BELOW 🖌 DO Uncoil cable before use 🚺 DON'T Allow heavy tools etc to hang unsupported on the cable or from the socket Position the cable carefully to avoid accidents **X DON'T**

🖌 DO 🚺 DON'T

- Use in wet conditions
- 🚺 DON'T
- Remove the plug and wire directly into a mains supply Exceed the total maximum load.

Masterplug Help Line 03300 249 279

Supplied by Luceco PLC Stafford Park 1 Telford TF3 3BD ENGLAND

Visit our website at

www.masterplug.com