

Heathfield 8W Cedar led emergency 2D range

Features In Brief:

- 1. Energy saving exceeding 50%
- 2. Uniformed light distribution
- 3. Original Epistar 3014 chips
- 4. Instant start, no flicking, no humming
- 5. Unique driver design
- 6. >10,000hrs (see website for details)
- 7. GR10q 2pin base



Heathfield LED 2d Emergency lamps are designed to replace the traditional fluorescent 2D lamp offering an energy saving alternative. The LED Board is constructed of high grade aluminium and the original Epistar3014 chips are powered by our own design driver to ensure stable operation and low levels of optical decay. The emergency requires an 24 hour charge and will provide up to five hours emergency lighting.

| Part Number | Colour | Luminous Flux |
|--------------------|--------|---------------|
| | | |
| H82D/LED/EME/4000K | 4000K | 790 lm |

Unit O, Westmead Ind Est, Westmead Drive, Swindon, Wiltshire, SN5 7YT T 01793 617376 | E info@heathfieldled.co.uk | www.heathfieldled.co.uk




Heathfield 8W Cedar led emergency 2D Features

8w Range

| ltem | H82D/LED/EME/4000K | |
|-----------------------|--------------------|--|
| Input voltage | 110-244V | |
| Power consumption | 8W | |
| Colour temperature | Cool white | |
| Life time | >10,000 hrs | |
| Operating temperature | -10°C to + 60°C | |
| Storage temperature | -10°C to + 65°C | |
| Lumen | 790lm | |
| Emergency wattage | 3W | |
| Emergency hours | Up to 5 hours | |
| Charge time | 8 hours | |
| Beam angle | 120° | |
| CRI | 80 | |

Chromaticity diagram



8W 2D emergency lamp image



Unit O, Westmead Ind Est, Westmead Drive, Swindon, Wiltshire, SN5 7YT T 01793 617376 | E info@heathfieldled.co.uk | www.heathfieldled.co.uk